

**Radio Nurse  
Call Transmitter  
ATX3000**



# Radio Nurse Call Transmitter ATX3000

Aid Call Ltd Healthcare Communications • Linhay House • Linhay Business Park • Ashburton • Devon TQ13 7UP  
**FREEPHONE 0800 052 3616** • T 01364 651593 • F 01364 651451 • E [healthcaresales@aidcall.co.uk](mailto:healthcaresales@aidcall.co.uk)  
[www.aidcall.co.uk](http://www.aidcall.co.uk)

The ATX3000 comes complete with a pull cord and 2 sockets for pear push leads or auxiliary trigger devices which include an optional pear push lead and cradle.

#### Infra Red Receiver

- The ATX3000 has a built-in infra red receiver that enables it to be remotely activated using the Buddy infra red transmitter.

#### Reassurance

- Reassurance flashing light on activation of unit (can be disabled)
- Reassurance sounder on activation of unit (can be disabled)

#### Call Types

- Call, Assistance, Emergency, Cancel, Low Battery and Fault (test signal), Nurse Presence (optional)

#### Code Combination

- 999 programmable room codes
- 999 house (site) codes

#### Inputs

- Auxiliary input terminals for accessories

#### Power Supply

- 4xAA alkaline batteries or external 6v DC supply

#### Operating Frequency

- 173.225 Mhz

#### Operating Temperature

- 0° to 40°C

#### Storage Temperature

- -25° to 75°C

#### Size

- Width 92mm x length 190mm x depth 36mm

#### Weight

- 310gms

#### Case

- ABS moulded

#### Standards

- Conforms to all relevant EC standards
- MPT1344
- EMC
- RoHS/WEEE compliant